

Quick Link: www.fair-rite.com/cb

Medium Current

Part Number	✓	Pkg. Size	Impedance (Ω)				Signal Speed	Max DCR (Ω)	Max Current (mA)
			50 MHz	100 MHz ⁺	500 MHz	1000 MHz			
2506033007Y3	✓	0603 (1608)	23	30 ±25%	40	41	Standard	0.040	3000
2506036007Y3	✓	0603 (1608)	48	60 ±25%	84	81	Standard	0.040	3000
2506031217Y2	✓	0603 (1608)	90	120 ±25%	170	152	Standard	0.050	2000
2508053007Y3	✓	0805 (2012)	23	30 ±25%	41	41	Standard	0.030	3000
2508056007Y3	✓	0805 (2012)	49	60 ±25%	84	84	Standard	0.040	3000
2508051217Y3	✓	0805 (2012)	91	120 ±25%	165	135	Standard	0.050	3000
2508053017Y3	✓	0805 (2012)	239	300 ±25%	218	117	Standard	0.050	3000
2508056017Y2	✓	0805 (2012)	449	600 ±25%	293	159	Standard	0.100	2000
2508051027Y1	✓	0805 (2012)	764	1000 ±25%	402	216	Standard	0.300	1000
2508052027Y1	✓	0805 (2012)	599	2000 ±25%	350	189	Standard	0.300	1000
2512063007Y3	✓	1206 (3216)	24	30 ±25%	40	38	Standard	0.030	3000
2512065007Y3	✓	1206 (3216)	39	50 ±25%	69	70	Standard	0.030	3000
2512067007Y3	✓	1206 (3216)	53	70 ±25%	102	103	Standard	0.040	3000
2512061517Y3	✓	1206 (3216)	120	150 ±25%	173	130	Standard	0.050	3000
2512063017Y3	✓	1206 (3216)	212	300 ±25%	150	88	Standard	0.060	3000
2512066017Y1	✓	1206 (3216)	460	600 ±25%	260	120	Standard	0.080	1000
2512061027Y1	✓	1206 (3216)	925	1000 ±25%	210	117	Standard	0.300	1000
2518066007Y3	✓	1806 (4516)	44	60 ±25%	91	94	Standard	0.040	3000
2518068007Y3	✓	1806 (4516)	64	80 ±25%	114	114	Standard	0.040	3000
2518127007Y3	✓	1812 (4532)	54	70 ±25%	96	96	Standard	0.040	3000
2518121217Y3	✓	1812 (4532)	92	120 ±25%	150	106	Standard	0.040	3000