


Feed-through terminals

WDU 70/95/...



Drill template for direct fitting
232 A/95 mm²

LR DNV

81/132/108 (block of 3)*

30 mm/M 8/S 6

1000 V/232 A/95 mm²

8 kV/3

6...12

16

16...120²⁾

16...95²⁾

16...95²⁾

16...50

3 x 9 x 0.8 6 x 9 x 0.8

4 x 16 x 0.8 6 x 16 x 0.8

16...120

B 12

232


(3) 232

600 V/175 A/6...2/0 AWG

600 V/205 A/6...2/0 AWG

Type	Cat. No.	Qty.
WDU 70/95/...	1026700000 ¹⁾	4
WDU 70/95/...	1026800000 ¹⁾	3
WDU 70/95/...	1026900000 ¹⁾	2
WDU 70/95/...	1032300000 ¹⁾	2
Type	Cat. No.	Qty.
WQV 70/2	1063500000	5
WQV 70/3	1063600000	5

WDU 120/150



309 A/150 mm²

LR DNV

32/132/118

35 mm/M 10/S 6

1000 V/269 A/120 mm²

8 kV/3

10...20

—

35...150

35...150

35...95

35...50

3 x 9 x 0.8 6 x 9 x 0.8

4 x 16 x 0.8 6 x 16 x 0.8

35...150

B 13

292


(3) 292

600 V/225 A/2...250 kcmil AWG

600 V/285 A/2...250 kcmil AWG

Type	Cat. No.	Qty.
WDU 120/150	1024500000	10
WDU 120/150	1024580000	10
WDU 120/150	1024550000	10

WDU 120/150/...



Drill template for direct fitting
309 A/150 mm²

LR DNV

96/132/118 (block of 3)*

35 mm/M 10/S 6

1000 V/269 A/120 mm²

8 kV/3

10...20

—

35...150

35...150

35...95

35...50

3 x 9 x 0.8 6 x 9 x 0.8

4 x 16 x 0.8 6 x 16 x 0.8

35...150

B 13

292

(3) 292

600 V/225 A/2...250 kcmil AWG

600 V/285 A/2...250 kcmil AWG

Type	Cat. No.	Qty.
WDU 120/150/...	1026400000 ¹⁾	3
WDU 120/150/...	1026500000 ¹⁾	2
WDU 120/150/...	1026600000 ¹⁾	2
WDU 120/150/...	1032400000 ¹⁾	2
Type	Cat. No.	Qty.
WQV 120/2	1063300000	5
WQV 120/3	1063400000	5

¹⁾ Terminal block for direct fitting only

²⁾ Using 95 and 120 mm² with 10 Nm tightening torque